

# Vx805 Blank Download Screen Fix

F1, F2, F3 and F4 are NOT used to Navigate!

Use this procedure if Vx805 shows a blank screen after choosing TCPIP on a CXPI download.

DURING DOWNLOAD STEPS

PRESS 6 (TCPIP)

VTM DOWNLOAD MGR G1

1> Modem	F1
2> COM1	F2
3> COM7	F3
4> SD Card	F4
5> USB Flash Memory	
6> TCPIP	

↓      ↓      ↑  
MORE | TIP | ALPHA | REPRINT | REPORT

RESULTS IN THE BELOW

	F1
	F2
	F3
	F4

MORE | TIP | ALPHA | REPRINT | REPORT

POWER CYCLE THE VX805

PRESS F2 & F4 TOGETHER

Download Needed  
NO \*GO Variable /  
Parameter

F1
F2
F3
F4

MORE | TIP | ALPHA | REPRINT | REPORT

KEY PASSWORD

1 ALPHA ALPHA 66831

PRESS ENTER

VERIX MGR ENTRY

Please Enter Password	F1
-----	F2
	F3
Press CANCEL to exit	F4

↓      ↑  
MORE | TIP | ALPHA | REPRINT | REPORT

PRESS 6 (Clear Memory)

VERIX TERMINAL MGR

1> Restart	F1
2> Edit Parameters	F2
3> Download	F3
4> Memory Usage	F4
5> Directory Listing	

Important Note:

Download requires special cable  
Part# CBL282-006-XX-B  
to connect Vx805 directly to IP  
(XX = 01-04 for Length of Cord)

F2 & F4 Alternative:  
Enter & 7

Some prompts may vary.

Default Password  
1 ALPHA ALPHA 66831

Secondary Passwords  
12345  
23378463

Last 9 digits (8,7,6,etc) of Previous  
Merchant Number

Download Addresses:

VC.FIRSTDEPLOY.COM  
Port: 443 - SSL

Alternate Download Addresses:

VC.FIRSTDEPLOY.COM  
Port: 8013 - TCPIP

VCPROD.FIRSTDATA.COM  
Port: 443 - SSL



	<b>6&gt; Clear Memory</b> <div> <div>↓</div> <div>↑</div> <div>↓</div> <div>↑</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
PRESS ENTER	<b>VERIX TERMINAL MGR</b> <div> <div>Group ID: __1</div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
KEY PASSWORD 1 ALPHA ALPHA 66831 PRESS ENTER	<b>VERIX TERMINAL MGR</b> <div> <div>Please enter Password for GID 1 -----</div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
PRESS 1 (Clear CONFIG.SYS)	<b>VTM DOWNLOAD MGR</b> ____ G1 <div> <div>1&gt; Clear CONFIG.SYS</div> <div>2&gt; Clear Split Files</div> <div>3&gt; Clear GID Files</div> <div>4&gt; Clear all Groups</div> <div>↓</div> <div>↑</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
PRESS 1 (Clear All)	<b>VTM DOWNLOAD MGR</b> ____ G1 <div> <div>1&gt; Clear All</div> <div>2&gt; Keep Protected Var</div> <div>↓</div> <div>↑</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
TERMINAL WILL FLASH THE FOLLOWING ON THE SCREEN	<b>VTM DOWNLOAD MGR</b> ____ G1 <div> <div>Clearing CONFIG.SYS</div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>
PRESS CANCEL UNTIL...	<b>VTM DOWNLOAD MGR</b> ____ G1 <div> <div>1&gt; Clear All</div> <div>2&gt; Keep Protected Var</div> </div> <div> <div>F1</div> <div>F2</div> </div>

		F3
		F4
	<div> <div>↓</div> <div>↑</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	
PRESS 3 (Download)	<div>VERIX TERMINAL MGR</div> <div> <div>1&gt; Restart</div> <div>2&gt; Edit Parameters</div> <div>3&gt; Download</div> <div>4&gt; Memory Usage</div> <div>5&gt; Directory Listing</div> <div>6&gt; Clear Memory</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>↓</div> <div>↑</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	
PRESS ENTER	<div>VERIX TERMINAL MGR</div> <div> <div>Group ID: __1</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	
KEY PASSWORD 1 ALPHA ALPHA 66831 PRESS ENTER	<div>VERIX TERMINAL MGR</div> <div> <div>Please enter</div> <div>Password for GID 1</div> <div>-----</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	
PRESS 1 (Single-app)	<div>VTM DOWNLOAD MGR _____ G1</div> <div> <div>1&gt; Single-app</div> <div>2&gt; Multi-app</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>↓</div> <div>↑</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	
PRESS 1 (Full dnld)	<div>VTM DOWNLOAD MGR _____ G1</div> <div> <div>1&gt; Full dnld</div> <div>2&gt; Partial dnld</div> </div> <div> <div>F1</div> <div>F2</div> <div>F3</div> <div>F4</div> </div> <div> <div>↓</div> <div>↑</div> </div> <div> <div>MORE</div> <div>TIP</div> <div>ALPHA</div> <div>REPRINT</div> <div>REPORT</div> </div>	

<b>TERMINAL MAY PROMPT:</b>  <b>PRESS 2</b> <b>(Continue)</b>	VTM DOWNLOAD MGR _____ G1	
	**** WARNING ****	F1
	All Files Will Be	F2
	Cleared From Group 1	F3
	1> Cancel Download	F4
	2> Continue	
	↓      ↑	
	MORE   TIP   ALPHA   REPRINT   REPORT	
	VTM DOWNLOAD MGR _____ G1	
	DELETING FILES	F1
		F2
		F3
		F4
	MORE   TIP   ALPHA   REPRINT   REPORT	
	VTM DOWNLOAD MGR _____ G1	
<b>PRESS 6 (TCPIP)</b>	1> Modem	F1
	2> COM1	F2
	3> COM7	F3
	4> SD Card	F4
	5> USB Flash Memory	
	6> TCPIP	
	↓      ↓      ↑	
	MORE   TIP   ALPHA   REPRINT   REPORT	
<b>NETWORK CONTROL PANEL</b> <b>SHOULD NOW LOAD</b> <b>ALLOWING YOU TO PROCEED</b>	Please Select	
	Download FTP	F1
		F2
		F3
		F4
	↑      ↓	
	MORE   TIP   ALPHA   REPRINT   REPORT	
<b>Proceed with Full Download Steps</b>		